

NEC

DSX

JetWave SIP Trunk Setup

April 23, 2011

Issue 1.01

©Copyright 2011

NEC Corporation of America
 6535 N. State Highway 161
 Irving, TX 75039-2402

Communications Technology Group

Revision History		
Issue	Date	Revisions
1.00	3/18/11	<ul style="list-style-type: none"> Initial release.
1.01	4/23/11	<ul style="list-style-type: none"> Updated required software level, expanded RTP port forwarding range, and added System Administrator screen shots. Removed requirement for 1104-09. Line Phone Numbers should now be a DID number provided by Jetwave, not a username.

Contents

1 Overview..... 4

2 JetWave Setup 4

3 System Router Setup..... 4

3.1 NAT and SIP..... 4

3.2 Port Forwarding 4

4 DSX Setup 4

4.1 Software Level 4

4.2 Assign SIP Lines..... 5

4.3 Select the SIP Trunk Provider Type 6

4.4 Set Up the SIP Trunk Registration..... 6

4.5 Codec Setup 7

4.6 Assign Phone Numbers to your SIP Lines..... 7

4.7 Outgoing Caller ID 7

4.8 Fax Setup 7

Tables

Table 1: JetWave Account Information 4

1 Overview

The DSX is compatible with JetWave SIP Trunking. This setup guide summarizes the account information you will receive from JetWave and provides step-by-step instructions on how to program that information into the DSX.

You must set up JetWave SIP trunks as DID lines. All the feature available with other types of DID lines are also available with JetWave SIP trunk lines. For details on the features available with DID lines, refer to the on-line DSX Software Manual at: http://www.necdsx.com/docs/dita/dsx_v3_complete/index.html

2 JetWave Setup

To set up your SIP trunking account, contact JetWave at <http://www.jetwaveservices.com>. Once your account is set up you need the service information:

Table 1: JetWave Account Information

Option	Description
Server Address	The Server Address is the SIP registration domain for your JetWave SIP trunks. When your SIP trunks initially register they use this address.
Username	This is the username that JetWave uses to authenticate your registration.
Password	This is the password required with your Login.
DID Number(s)	These are the telephone numbers that users will dial to reach you over your JetWave SIP trunks.

3 System Router Setup

3.1 NAT and SIP

In the router to which the DSX is connected, enable NAT and disable all special SIP management features (such as SIP ALG).

3.2 Port Forwarding

Forward UDP ports 5060 and 1024 through 1215 to the DSX system’s IP address.

4 DSX Setup

4.1 Software Level

3.31.96 or higher.

4.2 Assign SIP Lines

IP Line Assignment (1231/1232/1233)

Line	Name	Phone Number	Registered	Provider	Fax/Data	Description	Username	Password
1				None ▼	<input type="checkbox"/>			
2				None ▼	<input type="checkbox"/>			
3				None ▼	<input type="checkbox"/>			
4				None ▼	<input type="checkbox"/>			
5				None ▼	<input type="checkbox"/>			
6				None ▼	<input type="checkbox"/>			
7				None ▼	<input type="checkbox"/>			
8				None ▼	<input type="checkbox"/>			

1231-01: IP Lines [SYSTEM: PORTS: IP LINES: IP LINE ASSIGNMENT]

The first DSX SIP line is the first line beyond the last assigned line. Each SIP line uses an IP resource (licensed VoIP port) in DSX. The maximum number of VoIP licenses is 8 in DSX-40 and 16 in DSX-80/160.

Example with DSX-40:

- The first SIP line in a DSX-40 without a COIU expansion card is line 5. Available SIP line numbers are 5-12.
- With the COIU expansion card installed, the first SIP line is line 9. Available SIP line numbers are 9-16.
- DSX-40 supports a maximum of 8 VoIP licenses. When the total number of licenses are in use, only Peer-to-Peer calls are available.

Example with DSX-80/160:

- The first SIP line in a DSX-80/160 with a single 8COIU card is line 9. Available SIP lines are 9-17.
- The last line number in DSX-80/160 is 64. In a system with an 8COIU and two T1/PRI cards, this will limit the available number of SIP lines.
- DSX-80/160 supports a maximum of 16 VoIP licenses. When the total number of licenses are in use, only Peer-to-Peer calls are available.

1232-01: IP Line Provider Number [SYSTEM: PORTS: IP LINES: IP LINE ASSIGNMENT]

Assign each SIP line in DSX to a provider number (1 or 2). DSX supports up to two providers simultaneously.

Example: If JetWave is your only SIP trunk provider, assign all the SIP lines designated in 1231-01 to provider 1.

1232-02: IP Line Username [SYSTEM: PORTS: IP LINES: IP LINE ASSIGNMENT]

1232-03: IP Line Password [SYSTEM: PORTS: IP LINES: IP LINE ASSIGNMENT]

These options are not used with JetWave SIP trunks.

4.3 Select the SIP Trunk Provider Type

Provider 1 IP Service (1831) / IP Line Registration (1832)

Service Provider	Generic Sip	Description	
Server Address		Proxy Address	
Registration Type	None	User	
User		Password	
Profile	4	Name	SIP Trunk
SIP TOS	0	RTP TOS	0

1831-01: Provider Number [SYSTEM: VOIP: PROVIDERS: PROVIDER (1 OR 2)]

Select the provider number you want to set up. This selection corresponds to the provider number you assigned to the SIP lines in 1232-01.

Example: If JetWave is your only SIP trunk provider, and you have chosen provider 1 in 1232-01, select provider 1 for this option also.

1831-02: Provider Type [SYSTEM: VOIP: PROVIDERS: PROVIDER (1 OR 2): SERVICE PROVIDER]

Dial 13 to choose *Jetwave* as the type for the provider selected in 1831-01.

1831-03: Provider Name [SYSTEM: VOIP: PROVIDERS: PROVIDER (1 OR 2): DESCRIPTION]

The provider name is an optional 18-character entry that describes the provider. Enter any name you like – the entry does not affect provider setup or registration.

1831-04: Profile [SYSTEM: VOIP: PROVIDERS: PROVIDER (1 OR 2): PROFILE]

Select the VoIP profile that the system will use when connecting to the SIP trunk provider. The entry you make here corresponds to the profiles set up in programs 1811-1815. **Choose profile 4.**

4.4 Set Up the SIP Trunk Registration

1832-01: Provider IP Registration [SYSTEM: VOIP: PROVIDERS: PROVIDER (1 OR 2): SERVER ADDRESS]

Select the provider number you want to set up (see 1831-01) and enter the Table 1 *Server Address* as it was provided to you by JetWave. This option uses the text entry method.

1832-02: Registration Type [SYSTEM: VOIP: PROVIDERS: PROVIDER (1 OR 2): REGISTRATION TYPE]

Choose the IP line registration type. DSX IP lines can share the same registration (*01: Common*) or have a unique registration for each line (*02: Per Line*). For JetWave, choose *01: Common*.

1832-03: Account Username [SYSTEM: VOIP: PROVIDERS: PROVIDER (1 OR 2): USER]

Enter the username for your JetWave SIP trunk account. This option uses the text entry method and is the *Username* entry in Table 1.

1832-04: Account Password [SYSTEM: VOIP: PROVIDERS: PROVIDER (1 OR 2): PASSWORD]

This option is the password associated with the Account Username assigned in 1832-03. The password can be up to 24 characters long. This is the *Password* entry in Table 1.

1832-05: Proxy [SYSTEM: VOIP: PROVIDERS: PROVIDER (1 OR 2): PROXY ADDRESS]

1832-06: SIP Type or Service (ToS) [SYSTEM: VOIP: PROVIDERS: PROVIDER (1 OR 2): SIP TOS]

1832-07: RTP Type of Service (ToS) [SYSTEM: VOIP: PROVIDERS: PROVIDER (1 OR 2): RTP TOS]

These options are not used with JetWave SIP trunks.

4.5 Codec Setup

Profile Name (1811)

Codecs (1812)

Priority	Codec	Frame Size	Jitter Minimum	Jitter Standard	Jitter Maximum	Silence Compression
1	G.711	40ms	40	80	160	<input type="checkbox"/>
2	None		40	80	160	<input type="checkbox"/>
3	None		40	80	160	<input type="checkbox"/>
4	None		40	80	160	<input type="checkbox"/>
5	None		60	120	240	<input type="checkbox"/>
6	None		30	60	120	<input type="checkbox"/>

* Additional Codecs provided for 3rd party SIP phones

Settings (1813)

Jitter Mode Silence Threshold Idle Noise Tx Gain Rx Gain

Echo Canceller (1814)

Echo Cancel Enable Echo Tail NLP Enable NLP Noise Mode Auto Gain Control

Payload Types (1815)

DTMF Type DTMF Payload (96 - 127) ILBC Payload (96 - 127) G.726 Payload (96 - 127)

1812: Codecs [SYSTEM: VOIP: PROFILE 4: CODECS]
 For JetWave SIP Trunks, for Profile 4 set:
 - Codec 1 to G.711, 40mS Frame Size.

Set all other priorities to *None*.

4.6 Assign Phone Numbers to your SIP Lines

Type (3101)

Type Name DTMF Dialing PBX Line

Phone Number

3101-07: Telephone Number [LINES: CONFIG: SETUP: TYPE: PHONE NUMBER]
 For each of your SIP lines, enter a *DID Number* from Table 1 as the Phone Number entry.

4.7 Outgoing Caller ID

JetWave delivers Caller ID to outside callers using the following priority:

1. **2101-01: Outgoing ANI ID** [STATIONS: CONFIG: SETUP: TYPE: ANI ID]
2. **3101-07: Telephone Number** [LINES: CONFIG: SETUP: TYPE: PHONE NUMBER]
3. **1011-02: Telephone Number** [SYSTEM: CONFIG: SETUP: IDENTIFICATION: PHONE NUMBER]

4.8 Fax Setup

Contact JetWave for fax solutions. Normally, you should not use your JetWave SIP trunks for fax.